



PROJECT:	
LOCATION:	
MODEL#:	TYPE:
CLIENT:	QTY:
PREPARED BY:	DATE:

LSJBA-1

SERIES SPECIFICATIONS

The J-box PIR emergency unit is a new product in the emergency lighting field. It is a perfect combination of traditional emergency lighting and passive infrared-sensing technology that can be used as a combination PIR lamp and emergency unit or strictly as an emergency unit. It is a breakthrough in traditional emergency design, installing directly into a 4 Inch J-box. Colored faceplates are available. The passive infrared sensing (PIR) technology will activate when ambient light levels lower than 1.3FC are detected. The PIR has an activation distance of 15 feet with a 125 degree field of view. Once activated, the light will stay on for 15 minutes and then automatically turn off. The unit will automatically switch to emergency mode when AC power is lost.



ELECTRICAL SPECIFICATIONS

Rated Input Voltage: 120VAC / 277VAC
Wattage: 2.5W

SHIPPING SPECIFICATIONS

Package

Length: 7 in.